


Übergangsmuffe I.G.



d - Rp	L	Z	Gewicht in g
15-Rp $\frac{1}{2}$	53	20	52
15-Rp $\frac{3}{4}$	67	33	81
18-Rp $\frac{1}{2}$	51	18	52
18-Rp $\frac{3}{4}$	57	23	77
22-Rp $\frac{1}{2}$	52	17	77
22-Rp $\frac{3}{4}$	56	20	75
22-Rp1	70	31	105
28-Rp $\frac{3}{4}$	73	36	105
28-Rp1	62	22	103
28-Rp1 $\frac{1}{4}$	80	39	171
35-Rp1	81	38	136
35-Rp1 $\frac{1}{4}$	72	28	170
35-Rp1 $\frac{1}{2}$	83	39	259
42-Rp1 $\frac{1}{4}$	94	45	221
42-Rp1 $\frac{1}{2}$	74	25	252
54-Rp1 $\frac{1}{2}$	106	52	328
54-Rp2	84	25	342